



Micro AMP2 - Speaker and headphone amp

Micro AMP 2 is a dual amplifier.

The first is a class B amplifier in bridge mode (BTL) for the speakers. The maximum power delivered is 2x25W up into 4 Ohms, 2x40W up into 2 Ohms.

The second is a headphone amplifier capable of delivering 250mW continuous power into 8 ohms with 0.1% THD + N. At the rear you have a double entry in RCA or mini-jack 3.5 and a postpositionment to connect RCA audio amplifier or other audio systems.

Power supply is also doubled to power other devices from the same power supply.

Each amplifier has its own independent volume control.



Micro AMP4 - Headphone amp

Micro AMP 4 is a 4 channel headphone amplifier capable of delivering a continuous power 250mW into 8 ohms with 0.1% THD + N.

Each of the four amplifiers has its volume control. At the rear you have a double entry in RCA or mini-jack 3.5 and a postpositionment audio RCA and mini-jack 3.5 for connecting other amplifiers.

Power supply is also doubled to power other devices from the same power supply.



SPECIFICATION

Amplifier 1: For Speakers

- 2x40W / 2 ohms (10% THD) @ 15V DC
- 2x25W / 4 ohms (10% THD) @ 15V DC
- Thermally protected
- Load 2 to 8 ohms

Amplifier 2: For headphone

- 2x375mW / 8 ohms (10% THD)
- Thermally protected
- Load from 8 to 32 Ohms

Connectors:

- RCA audio input
- Audio input minijack 3.5 stereo
- RCA audio output (link)
- Speaker Output Terminal Block
- Stereo headphone output jack 6.35
- 12V DC power supply (7V to 16V)

SPECIFICATION

- 4 independent headphone amplifiers
- Volume for each channel
- 375mW / 8 ohms (10% THD)
- Thermally protected
- Load from 8 to 32 Ohms

Connectors:

- RCA audio input
- Audio input minijack 3.5 stereo
- RCA audio output (link)
- Mini-jack audio output 3.5 (link)
- Headphone output mini-jack 3.5 stereo
- 12V DC power supply (7V to 16V)

SPECIFICATIONS

- Metal Shelf 19" / 1U
- Up to 3 modules
- Depth 120 mm (also available in 171mm depth)
- Protective covers available



You can put the Micro AMP 2 and 4 in 19" rack with shelf option. You insert up to 3 modules in 1U and use the other products in the range as MicroPlayer, EventPlayer, My Music Player and other compatible products.