

# MY MUSIC STATION

Sept 2011



## Standalone Audio Player for unattended broadcast.

The My Music Station has been designed to broadcast, automatically and unattended, a large volume of music and messages. The system reads MP3 and Wav files stored in a hard disk, USB flash Memory or a SD Card and plays tracks in random or sequential mode. You can also create M3U playlist to control your music.

My Music Station is the ideal solution for broadcasting background music and commercial / promotional pre-recorded messages. Using the free ID-AL Scheduler software, you can create a grid for each day to control the player. (Play message, change music style, modify volume, select a web radio, select Aux input ...)

You can update the media with the USB link and a computer, replace easily the media or using ethernet link (FTP upload and download) or insert a CD/DVD to transfer the new files.

My Music Station is a complete and reliable solution, easy to use, low consumption, usable 24/24 - 7/7 including many functions and many tools for music providers,

With the RS232 link, you can control all the the players from a programmable controller.

My Music Station is a cost effective solution for broadcasting customised in-store radio in shops or restaurants.

### Suggestions :

- Installed in shops, restaurants, bars, hotels, waiting places, car parks, tube stations, My Music Player broadcast programmed background music and public information messages...

### Specifications

- Reads MP3 files from 64kbps to 320kbps and Wav files 44,1/48/96kHz - 16/24 bits

#### Supported medias (not provided) :

- External : USB flash memory
- Internal : Hard disk SATA 2"1/2, USB stick, SD/SDHC Card,

#### Ethernet :

- FTP server and client (upload et download)
- Web server (http) - Administration
- SAMBA Server
- Play Web Radio / streaming
- NTP protocol (universe time)
- DHCP Mode
- Send email in case of error
- RSS

#### Misc :

- USB 2.0 High Speed to update internal HDD
- CD/DVD drive to update HDD and play music
- Infrared remote control
- RS232 control
- 5 bands EQ
- Complete keyboard with transport and preset
- Automatic Summer/Winter time
- Fade in/out (from/to AUX input)
- Programmable front face push buttons
- Low consumption
- Autoplay mode when switch on
- LCD 2 x 16 characters display
- Designed and manufactured in France

#### Connection :

- Unbalanced output on RCA
- Unbalanced Aux input on RCA
- Amplified output 2 x 15W
- Ethernet RJ45 link
- RS232 serial link
- 12V DC PSU

#### Optionnal and free softwares :

- Scheduler (time programming)
- Script for automatic file copy
- Encryption MP3 file (under licence)

